

产品规格书

产品名称	单刀八掷开关		规格型号	HTSR8-19323																																				
技术指标	1	工作频率	19~32GHz																																					
	2	插入损耗	≤9dB																																					
	3	驻波	≤2																																					
	4	开关隔离	≥45dB																																					
	5	承受功率	≥20dBm																																					
	6	开关时间	≤200nS																																					
	7	工作方式	反射式																																					
电源及控制	1	电源	+5V/260mA & -5V/50mA																																					
	2	控制	3 位 TTL 电平																																					
接口形式	1	射频接口	2.92-K																																					
	2	控制及电源	J30J-9ZKP 1—+5V, 2—GND, 3—空, 4—-5V, 5—GND, 6—TTL0, 7—TTL1, 8—TTL2, 9—GND																																					
外形尺寸	<p style="text-align: right; margin-top: 10px;"> J30J-9ZKP 连接器位置可调整 表面处理: 本色导电氧化 产品标识: 刻字, 宋体, 字高 2mm </p>																																							
温度环境	1	工作温度	-40~+70℃																																					
	2	存储温度	-55~+85℃																																					
真值表	<table border="1" style="width: 100%; border-collapse: collapse; text-align: center;"> <thead> <tr> <th>TTL2</th> <th>TTL1</th> <th>TTL0</th> <th>功能</th> </tr> </thead> <tbody> <tr> <td>0</td> <td>0</td> <td>0</td> <td>J0 与 J1 导通</td> </tr> <tr> <td>0</td> <td>0</td> <td>1</td> <td>J0 与 J2 导通</td> </tr> <tr> <td>0</td> <td>1</td> <td>0</td> <td>J0 与 J3 导通</td> </tr> <tr> <td>0</td> <td>1</td> <td>1</td> <td>J0 与 J4 导通</td> </tr> <tr> <td>1</td> <td>0</td> <td>0</td> <td>J0 与 J5 导通</td> </tr> <tr> <td>1</td> <td>0</td> <td>1</td> <td>J0 与 J6 导通</td> </tr> <tr> <td>1</td> <td>1</td> <td>0</td> <td>J0 与 J7 导通</td> </tr> <tr> <td>1</td> <td>1</td> <td>1</td> <td>J0 与 J8 导通</td> </tr> </tbody> </table>				TTL2	TTL1	TTL0	功能	0	0	0	J0 与 J1 导通	0	0	1	J0 与 J2 导通	0	1	0	J0 与 J3 导通	0	1	1	J0 与 J4 导通	1	0	0	J0 与 J5 导通	1	0	1	J0 与 J6 导通	1	1	0	J0 与 J7 导通	1	1	1	J0 与 J8 导通
TTL2	TTL1	TTL0	功能																																					
0	0	0	J0 与 J1 导通																																					
0	0	1	J0 与 J2 导通																																					
0	1	0	J0 与 J3 导通																																					
0	1	1	J0 与 J4 导通																																					
1	0	0	J0 与 J5 导通																																					
1	0	1	J0 与 J6 导通																																					
1	1	0	J0 与 J7 导通																																					
1	1	1	J0 与 J8 导通																																					